


# VersaLog™

**Model:  
DCVC-HR**



16-bit analog-to-digital converter meets most high-resolution requirements

4-mega byte memory stores up to 2 million measurements

Seven range programmable voltage and current external input channels cover wide measurement requirements

Can be accessed via USB, MODEM, or Ethernet connections with auto baud rate of up to 115 kbps

10-year battery life

Fast sampling mode

Alarm and excitation output

The VersaLog DCVC-HR is an 8-channel, battery powered, stand-alone voltage/current DC data logger. It records up to 4 megabytes of data and stores it in non-volatile flash memory for later retrieval. Input voltage/current signals can be from sensors, transducers, transmitters or any other common voltage/current sources.

Featuring an aluminum enclosure, the VersaLog logger has excellent performance in the harshest industrial environment.

Powered by a 16-bit ADC and programmable input range, the VersaLog logger is well suited to science and laboratory applications where precise and accurate measurement is critical.

## SiteView Software

SiteView is a Windows-based application which works with the VersaLog Series data loggers for downloading, configuration, data analyzing and plotting. Its user-friendly graphic interface plus powerful functionalities fit both novice and advanced users.

The versatility of custom equation and custom-line equation handles complicated measurement requirements.

- Supports USB, Serial port and Ethernet connections for easy local and remote access
- Fast communication speed up to 115200 bps makes downloading fast

- Real-time viewing and chart recording replaces chart recording devices
- Custom equation and custom-line equation solves scientific and laboratory algorithm difficulties
- Zoom in/zoom out, annotation/label of graph functions provide detailed view of data
- Multiple file loading allows easy data comparison
- Dynamic statistics provide detailed information of current zoomed view

### Technical specifications (subject to change without notice)

Inputs	
Channels	CH1 ~ CH4 (voltage): programmable range for each: 0 ~ 20 V, 0 ~ 2 V, CH5 ~ CH7 (current) programmable range for each: 0 ~ 20 mA
Accuracy	Thermistor channel: reference temperature 0.36°F Voltage channels: +/- 0.05% FSR @ 25°C for 20V channels, +/- 0.1% FSR @ 25°C for 2V channels Current channels: +/- 0.15% FSR @ 25°C
Load Resistor	For current channel: 12 Ohms
Protection	Voltage channel: +/- 40 VDC, Current channel: +/-100 mA
Alarms	
Channel Alarms	Two editable alarm thresholds per channel
Alarm Outputs	ALARM1 & A2/EXT terminal strips can be configured as alarm outputs Alarm-On: MOSFET (N-Channel) switch on Alarm-Off: MOSFET (N-Channel) switch off Max Power: 200mA @ 24VDC Can report alarm status to host PC via USB, Modem or Ethernet Device Server with SiteView software <sup>[2]</sup>
Alarm-On Delay	Programmable 0 - 10 minutes delay with 1-minute increments
Alarm Indicator	On-board LED lights in red when in alarm condition
On-Board Memory	
Capacity	4MB ~ 2 million measurements
Data Retention	Over 20 years
Sampling & Logging	
Sampling Interval	20 milliseconds <sup>[1]</sup> to 12 hours user selectable
Logging Mode	Stop recording or FIFO when memory is full
Logging Activation	Programmable instant, start delay or field push-button activation

Communications	
Interface	USB (USB cable included), AUX (RJ11) for direct TTL level communications Can be connected to Ethernet for remote access with DeviceServer Kit <sup>[2]</sup>
Baud Rate	Auto-detect baud rate from 2400 to 115200 bps on both USB and AUX ports
Battery	
Power	Built-in 3.6V Lithium Battery
Life Cycle	10 years based on 1 minute sampling interval
Software	
SiteView <sup>[2]</sup>	Configuration, downloading, plotting, real-time view, custom calibration and custom equation
Software Requirements	Computer with 1.0 GHz or faster processor, 256 MB Memory or higher & 1.0 GB of available hard-drive space or higher Windows XP with SP2 or later, Vista, Windows 7, 8 At least one USB port or one COM port
Other	
LED Indicator	Normal Sampling: green when sampling Alarm: red when sampling Low Battery: amber when sampling
Excitation Control	A2/EXT terminal strip can be configured as excitation control output for powering connected devices Warm-up delay Interval settings: 10 to 240 seconds with 10-second increments
Operating Environment	-40 ~ +70°C (-40°F ~ 158°F), 0~95%RH non-condensing
Clock Accuracy	+/- 1 minute per month
Approvals	CE, FCC

[1]: Maximum enabled channel: 1 for 20ms interval, 2 for 30ms, 8 for 40ms or bigger interval.

[2]: Sold separately.